

## BATTEN - LITE



50,000  
Hours



5  
Years  
Warranty



ECA

The Bardsey Batten - Lite is designed for ease of installation, utilising a three-end wiring system. Boasting an impressive 115 lumens per Watt, this fitting complies with ECA regulations and is available with DALI, Sensors or Emergency.



- EM (Emergency) 3W Integral Emergency  
3 hours maintained duration

IP Rating	IP20
<b>Weight (kg)</b>	
18W/36W	1.6
30W/55W	2.0
40W/80W	2.5
<b>Dimensions (mm)</b>	
18W/36W	1175 x 58 x 78
30W/55W	1475 x 58 x 78
40W/80W	1775 x 58 x 78
<b>BESA FIXING CENTRES (mm)</b>	
(All versions)	300

- Benefits**
- Three-end wiring
  - ECA compliant
  - DALI, Sensor and Emergency options

- Applications**
- Corridors
  - Racking
  - Industrial

PART NO.	WATTAGE	DESCRIPTION	BEAM	EFFICACY	LUMENS	Ra/CCT	SYSTEM POWER
BTN025	18W	18W LED Bardsey Batten Lite, 1200mm, 840	120° x 150°	115	2,070	840	18W
BTN026	36W	36W LED Bardsey Batten Lite, 1200mm, 840	120° x 150°	115	4,140	840	36W
BTN027	30W	30W LED Bardsey Batten Lite, 1500mm, 840	120° x 150°	115	3,450	840	30W
BTN028	55W	55W LED Bardsey Batten Lite, 1500mm, 840	120° x 150°	115	6,325	840	55W
BTN029	53W	53W LED Bardsey Batten Lite, 1800mm, 840	120° x 150°	115	4,600	840	40W
BTN030	78W	78W LED Bardsey Batten Lite, 1800mm, 840	120° x 150°	115	9,200	840	80W

**+ Controls**

-CD DALI Dimmable

**+ Sensor**

-SL Sensor Low Level (up to 8m detection height)  
-SB Switching Sensor

**+ Emergency**

-EM Emergency  
-EMST Emergency Self-Test

**Accessories**

ACS153 Programming Remote for SB Sensor  
ACS067 Programming Remote for SH / SL Sensor versions  
ACS030 Commissioning Handset for SH / SL Sensor versions